

RR2-298-RMT-PAR16

Installation Instructions (Remodel)

CLARTÉ™

LIGHTING

CAUTION! READ AND FOLLOW ALL SAFETY AND INSTALLATION INSTRUCTIONS CAREFULLY. TURN OFF ELECTRICAL POWER BEFORE STARTING INSTALLATION.


WARNING - Before starting installation, disconnect power by turning off the circuit breaker or by removing the appropriate fuse at the fuse box. Do not install any luminaire assembly closer than 6" from any curtain or similar combustible materials. Risk of fire or electric shock. Luminaire wiring and electrical parts may be damaged when drilling for installation of LED retrofit kit. Check for enclosed wiring and components. Risk of fire or electric shock. LED Retrofit Kit installation requires knowledge of luminaires electrical systems. If not qualified, do not attempt installation. Contact a qualified electrician. Risk of fire or electric shock. Install this kit only in luminaires that have the construction features and dimensions shown in the photographs and/or drawings and where the input rating of the retrofit kit does not exceed the input rating of the luminaire. To prevent wiring damage or abrasion, do not expose wiring to edges of sheet metal or other sharp objects. Do not make or alter any open holes in an enclosure of wiring or electrical components during kit installation. **Consult a qualified electrician before installing. Work should be performed by qualified personnel.**

Suitable to install on **"Dimming Circuits"**.


SAVE THESE INSTRUCTIONS

Max of 6 fixtures to be wired in series

Light-Emitting Diode Lamp is fully Dimmable



1. Before starting installation, turn **off** electrical power to the existing fixture. Remove existing fixture (if applicable). Opening Must be 3.5" in Diameter.



2. Connect male connector to female MR16 socket. Connect the black and white wire to a 12V supply.



3. Push springs back and Insert fixture and springs into opening



4. Push Fixture into opening. There will feel spring resistance and fixture will snap in place.



5. Restore power and check the operation of your new **CLARTÉ** light fixture